

Art.No.	article name
433408006	KOPP Kuara 8.0-3-H: Three-phase hybrid inverter, rated power: 8000 W

KOPP Kuara 8.0-3-H: Three-phase hybrid inverter, with Kopp Smart WIFI dongle art. No. 4360.4005.2, rated power: 8,000 W/12.8 A; 2+1 MPP tracker, DC switch, max. PV generator power: 10.4 kWp, with Kopp Smart Meter Art. No. 4360.1002.0



Technical data		433408006
Height		519.0 mm
Wireless		no
Depth		198.0 mm
With transformer		no
Nominal output power AC		8000
Max. input current DC		40.00 A
Max. input voltage DC		1000 V
Max. input current DC per MPP tracker		26.00 A
Max. input current DC per string input		26.00 A
Integrated DC switch		no
Width		449.0 mm
Weight		28.000 kg
European efficiency		97 %
Max. input power DC		10400
Number of independent MPPT inputs		2
Suitable for emergency power		yes
Usable battery capacity		0 kWh
Degree of protection (IP)		IP65
Built-in battery		no
Display		LCD
Output phases		3-phase
Voltage type of supply voltage		AC
Ethernet		ja
MPP-spanning (Maximum Power Point)		160 950 V
Max. efficiency		98.00 %
CEC efficiency (US products)		0.00 %
With data logging		nein
Suitable for outdoor mounting		ja
String connetions per MPPT input		2
DC connection		Steckverbinder
AC connection		Steckverbinder
Max. short circuit current per MPPT		32.00 A

Technische Beschreibungen, Abbildungen und Leistungsangaben stellen keine zugesagten Eigenschaften dar, sondern sind nur unverbindliche Informationen. Änderungen aufgrund technischen Fortschritts, Normänderungen, veränderter Fertigungsverfahren oder Konstruktionsverbesserungen bleiben ausdrücklich vorbehalten. Stand: 28.02.2024