Art.No.	article name
432515002	KOPP Kuara 15.0-2-T: Three-phase inverter, rated power: 15000W

KOPP Kuara 15.0-2-T: Three-phase inverter with integrated WiFi, Rated power: 15000W; 2 MPP trackers, DC switch, max. PV generator power: 22. 5kWp

Technical data	*432515002*
Height	480.0 mm
Wireless	no
Depth	183.5 mm
With transformer	no
Nominal output power AC	15000
Max. input current DC	56.00 A
Max. input voltage DC	1100 V
Max. input current DC per MPP tracker	28.00 A
Max. input current DC per string input	28.00 A
Integrated DC switch	yes
Width	370.0 mm
Weight	17.000 kg
European efficiency	98 %
Max. input power DC	22500
Number of independent MPPT inputs	2
Suitable for emergency power	no
Usable battery capacity	0 kWh
Degree of protection (IP)	IP65
Built-in battery	no
Display	LCD
Output phases	3-phase
Voltage type of supply voltage	DC
Ethernet	nein
MPP-spanning (Maximum Power Point)	140 - 1000
Max. efficiency	98.6 %
With data logging	nein
Suitable for outdoor mounting	ja
String connetions per MPPT input	2
DC connection	Steckverbinder
AC connection	Steckverbinder
Max. short circuit current per MPPT	36.40 A

Technische Beschreibungen, Abbildungen und Leistungsangaben stellen keine zugesagten Eigenschaften dar, sondern sind nur unverbindliche Informationen. Änderungen aufgrund technischen Fortschritts, Normänderungen, veränderter Fertigungsverfahren oder Konstruktionverbesserungen bleiben ausdrücklich vorbehalten. Stand: *02.01.2026*