

Art.No.	article name
835005012	Smart-control Bluetooth LED controller, RGBW, RGB, W/R/G/B (Single), 4-Channel, colour: arctic white

Smart-control Bluetooth LED controller, RGBW, RGB, W/R/G/B (Single), 4-channel, Input: screw terminals or socket for power supply 12-24V, Output: screw terminals, max. 15A (up to 6A per channel), max. 360W (up to 72W - 144W per channel), colour: arctic white



Technical data	835005012
Current supply	12 - 24 V AC/DC
Number of relays	1
Suitable for switch	yes
Suitable for pulse button	no
Suitable for dimmer	yes
Suitable for roller shutter switch	no
Material	Plastic
Type of fastening	Screw mounting
Suitable for venetian-/roller shutter switch	no
Suitable for venetian shutter switch	no
Transparent	no
Compatible with Apple HomeKit	no
Compatible with Google Assistant	yes
Compatible with Amazon Alexa	yes
Mounting method	Surface mounted
Colour	White
Halogen free	no
Surface protection	Untreated
Rolling code system	no
Number of commands	∞
Radio frequency	2400
In housing	yes
In tube base housing	no
Printed circuit board/module	no
Push button mode	yes
Switching mode	yes
With manual radio transmitter	no
With radio coding device	no
With radio controlled push button	no
Code length (Bit)	128
RAL-number (similar)	9016
IFTTT support available	no
Degree of protection (IP)	IP20
Material quality	Polyamide (PA)

Technische Beschreibungen, Abbildungen und Leistungsangaben stellen keine zugesagten Eigenschaften dar, sondern sind nur unverbindliche Informationen. Änderungen aufgrund technischen Fortschritts, Normänderungen, veränderter Fertigungsverfahren oder Konstruktionsverbesserungen bleiben ausdrücklich vorbehalten. Stand: 29.02.2024

Technical data		835005012
Degree of protection (NEMA)	Other	
Surface finishing	Glossy	
Modulation	FM	
Farbe (Kopp-Bezeichnung)	arctic white	