

Art.No.	article name
842800187	Push-change over LED-dimmer, (phase control), LED 3 - 35 W

Push-change over LED-dimmer for light bulbs and 230 V halogenlight, as well as low voltage halogen light. Not for electronic transformer. Note transformer manufacturer´s recommendations. RL 7-110W/VA



Technical data	842800187
Frequency	50 50 Hz
Material	Plastic
Type of fastening	Mounting with claw and screw
Impact strength	IK00
Nominal voltage	230,00 230,00 V
Transparent	no
Dimming phase cut-off	no
Dimming phase cut-on	yes
Nominal power inductive load	7 110 VA
Compatible with Apple HomeKit	no
Compatible with Google Assistant	no
Compatible with Amazon Alexa	no
Max. switching power LED	35 W
Mounting method	EV000383 - Flush-mounted (plaster)
Assembly arrangement	Basic element
Method of operation	Turn/push button
Halogen free	yes
Surface protection	Untreated
Substation input	no
Serial dimmer	no
Applicable with movement sensor	no
Applicable with transmission button	no
Applicable with infrared button	no
Applicable with presence indicator	no
Applicable with button	no
Applicable with time switch/timer	no
IFTTT support available	no
Type of load	Inductive load
Surface finishing	Glossy
Suitable for degree of protection (IP)	IP20
Min. brightness controllable	ja